LED DRIVER Programmable 80W 0-10V Dimming

5-100% Output Range of 27V to 55V Current 1.05A to 2.1A Max **80W** Class 2 Short case with Leads

Universal Voltage 120-277V Electronic **Programmable (NFC)** LED Driver 0-10V Dimming **5-100%.** Output Range of 27V to 55V for Single circuit 80W maximum.

Technical Specification:

Class 2 UL, CUL Recognized, ROHS Compliant Input Voltage range: + 10% FCC Parts 18, Subparts C, Class A Output Load range + 5% IP 64 Damp 50/60HZ Rating: TL Input Frequency: Output Open/Short Protection THD: < 20% Min. Starting Temp: Power Factor Min: 0.90

Max. Case Temp: 90° C Remote Wiring Distance Full Load: 18AWG -18 ft

Typical Efficiency 90%

Case Size: Series FS3


Due to continuing efforts to offer improved products all specifications are subject to change without prior notice


INPUT VOLTAGE	INPUT CURRENT	INPUT WATTS	OUTPUT POWER WATTS MAX	OUTPUT VOLTAGE	OUTPUT CURRENT AMPS	MODEL
120	0.76	90	90	27 to 55V	1.05 - 2.1	PU2100C80WRSD5
277	0.33	89	80			


LIMITED WARRANTY

5 YEAR at maximum case temperature 75 deg C. 3 YEAR at maximum case temperature 90 deg C. Manufacturer warrants to the purchaser: Product will be free from defects in material or workmanship from the date of manufacture conditioned upon proper storage, installation, use, and maintenance and conformance with any recommendations of Manufacturer

Lead Length						
Colour	inch	cm				
Black	5.9	15				
White	5.9	15				
Blue	5.9	15				
Red	5.9	15				
Gray	5.9	15				
Purple	5.9	15				







Place the Programmable wand above the NFC Mark on the LED Driver to start programming

WARNING: Always Disconnect Power Before Handling.

Case Should be Grounded. Install in Accordance
with National and Local Electrical Codes.

241

 Series FS3
 L
 W
 H
 ML

 Case Size:
 241mm
 61 mm
 37 mm
 226mm

 9.5inch
 2.4inch
 1.46inch
 8.9inch

1500 Marine Drive, #200 North Vancouver, BC V7P 1T7

TEL: 604-904-9533 FAX: 604-904-9634

EMAIL: sagelighting@shaw.ca www.sagelighting.com

